

DARAMIO

Modern LED-Lit Mirrors for Every Interior.

SmartScreen + Google TV

Operating Instructions

SmartScreen + Google TV

TECHNICAL CHARACTERISTICS

- Stream music and videos via Google TV to the integrated 10" SmartScreen screen in the Artalo mirror. It only takes a few minutes to activate your Smart device using your smartphone or tablet. You can then operate the SmartScreen with the remote control (supplied with the mirror) and easily launch services such as Netflix, HBO Max, YouTube or Spotify. Lots of other apps can be easily downloaded on Google Play. Google TV can also be controlled with your smartphone or tablet. The mirror is equipped with an integrated bluetooth speaker, and it is also possible to connect external speakers. The surface of the mirror in the SmartScreen area is completely transparent, so you will see a clear image.

WIRING INSTRUCTIONS

1. You'll need a mobile phone, tablet, or computer to connect your SmartScreen with Google TV.

2. Download the Google Home or Google TV app: Download and install the Google Home app on your device.

3. Launch the app.

4. Wait for Google TV to connect.

5. Select the Google TV device you want to connect.

6. Verify the code: A verification code will appear on the SmartScreen of the mirror and on your device. Once the code appears, click the "I SEE IT" button in the app.

7. In the last step, choose a device name in the settings.

SPECIFICATIONS

Parameters:	SmartScreen with Google TV
Manufacturer:	Google - Google TV
Screen size:	10"
Resolution:	1280×800px (HD)
Speakers:	Integrated in the mirror, external speakers can be connected
Control:	remote control (included), smartphone, voice
Switching on/off:	remote control
Voice commands:	Yes
Wifi:	Yes
Bluetooth:	Yes
App availability:	Apps from Google Play (Google TV OS)
System:	Google TV (Android TV OS)
Internal memory:	32 GB
RAM:	8 GB
External speaker connection:	Yes
Power:	Constant power, separate cable
Mirroring:	Android and iOS (Google Cast / Chromecast built-in)
Smartphone connectivity:	Google Home app, Google TV
Power consumption	~ 10 W
Component power supply	5 V DC
Input voltage of the power supply	230 V AC
Output voltage of the power supply	12 V DC

Recommended connection options for connecting the mirror to the power supply

Option 1:

Connection of the LED mirror lighting and the SmartScreen display to the power supply when selecting the touch button/sensor switch.

If you have selected another additional component for the mirror, the wiring diagram for its connection can be found in the manual for that specific component.



Option 2:

Connection of the LED mirror lighting and the SmartScreen display to the power supply when selecting an external switch.



Each component has its own manual with a wiring diagram.

Recommended connection options for connecting the mirror to the power supply

Option 3:

Connection of the LED mirror lighting and the SmartScreen display to the power supply when selecting an external switch on a single power cable.



When selecting the option where the mirror is powered by a single power cable:

the SmartScreen can only be turned on after the LED lighting has been switched on using the external switch.

Each component has its own manual with a wiring diagram.